



SP20 GNSS Handheld



User Guide



Legal Notices

©2018 Trimble Inc. All rights reserved.

All product and brand names mentioned in this publication are trademarks of their respective holders.

SP20 User Guide, Rev. A, August 2018.

Limited Warranty Terms and Conditions

Product Limited Warranty. Subject to the terms and conditions set forth herein, Trimble Navigation Limited ("Trimble") warrants that for a period of (1) year from date of purchase this Spectra Precision product (the "Product") will substantially conform to our publicly available specifications for the Product and that the hardware and any storage media components of the Product will be substantially free from defects in materials and workmanship.

Product Software. Product software, whether built into hardware circuitry as firmware, provided as a standalone computer software product, embedded in flash memory, or stored on magnetic or other media, is licensed solely for use with or as an integral part of the Product and is not sold. The terms of the end user license agreement govern the use of the Product Software, including any differing limited warranty terms, exclusions and limitations, which shall control over the terms and conditions set forth in the limited Product warranty.

Warranty Remedies. If the Product fails during the warranty period for reasons covered by this limited warranty and you notify us of such failure during the warranty period, we will repair OR replace the nonconforming Product with new, equivalent to new, or reconditioned parts or Product, OR refund the Product purchase price paid by you, at our option, upon your return of the Product in accordance with our product return procedures then in effect.

Notices

Class B Statement - Notice to Users. This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to Part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates, uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communication. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:

- Reorient or relocate the receiving antenna.
- Increase the separation between the equipment and the receiver.
- Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.
- Consult the dealer or an experienced radio/TV technician for help.

Changes or modifications not expressly approved by the manufacturer or registrant of this equipment can void your authority to operate this equipment under Federal Communications Commission rules.

Canada

The digital apparatus does not exceed the Class B limits for radio noise emissions from digital apparatus as set out in the radio interference regulations of the Canadian Department of Communications.

Le présent appareil numérique n'émet pas de bruits radioélectriques dépassant les limites applicables aux appareils numériques de Classe B prescrites dans le règlement sur le brouillage radioélectrique édicté par le Ministère des Communications du Canada.

NCC英文警語:

According to "Administrative Regulations of Low Power Radio Waves Radiated Devices:

Article 12 The low-power radio-frequency devices must not be altered by changing the frequency, enhancing emission power, adding external antenna, and modification of original design characteristic as well as function.

Article 14 The operation of the low-power radio-frequency devices is subject to the conditions that no harmful interference is caused. The user must stop operating the device immediately should harmful interference is caused and shall not resume until the condition causing the harmful interference has been corrected.

Moreover, the interference must be accepted that may be caused by the operation of an authorized communications, or ISM equipment.

Europe



This product has been tested and found to comply with the requirements for a Class B device pursuant to European Council Directive 89/336/EEC on EMC, thereby satisfying the requirements for CE Marking and sales within the European Economic Area (EEA). These requirements are designed to provide reasonable protection against harmful interference when the equipment is operated in a residential or commercial environment.

Notice to Our European Union Customers



For product recycling instructions and more information, please go to <http://www.spectraprecision.com/footer/weee-and-rohs/>.

Recycling in Europe: To recycle Spectra Precision WEEE (Waste Electrical and Electronic Equipment products that run on electric power), call +31 497 53 24 30 and ask for the "WEEE Associate". Or, mail a request for recycling instructions to:

Trimble Europe BV
c/o Menlo Worldwide Logistics
Meerheide 45
5521 DZ Eersel, NL

Declaration of Conformity

We, Spectra Precision,
declare under sole responsibility that the product:
SP20 GNSS handheld
complies with Part 15 of FCC Rules.

Operation is subject to the following two conditions:

- (1) this device may not cause harmful interference,
- (2) and this device must accept any interference received, including interference that may cause undesired operation.

Rechargeable Lithium-ion Battery

This receiver uses a rechargeable Lithium-ion battery.



WARNING - Do not damage the rechargeable Lithium-ion battery. A damaged battery can cause an explosion or fire, and can result in personal injury and/or property damage. To prevent injury or damage:

- Do not use or charge the battery if it appears to be damaged. Signs of damage include, but are not limited to, discoloration, warping, and leaking battery fluid.
- Do not expose the battery to fire, high temperature, or direct sunlight.
- Do not immerse the battery in water.
- Do not use or store the battery inside a vehicle during hot weather.
- Do not drop or puncture the battery.
- Do not open the battery or short-circuit its contacts.



WARNING - Avoid contact with a rechargeable Lithium-ion battery if it appears to be leaking. Battery fluid is corrosive, and contact with it can result in personal injury and/or property damage. To prevent injury or damage:

- If a battery leaks, avoid contact with the battery fluid.
- If battery fluid gets into your eyes, immediately rinse your eyes with clean water and seek medical attention. Do not rub your eyes!
- If battery fluid gets onto your skin or clothing, immediately use clean water to wash off the battery fluid.



WARNING - Charge and use the rechargeable Lithium-ion battery only in strict accordance with the instructions. Charging or using the battery in unauthorized equipment can cause an explosion or fire, and can result in personal injury and/or equipment damage. To prevent injury or damage:

- Do not charge a battery if it appears to be damaged or leaking.
- USE EXCLUSIVELY the AC/DC charger provided to charge the SP20 Lithium-ion battery. The charger output specification is 5 V - 2 A. See instructions in this guide.

CHARGE THE BATTERY ONLY IN THE TEMPERATURE RANGE 0° to +40°C (32° to 104°F), at a maximum altitude of 2,000 meters (6,562 feet).

- Discontinue charging a battery that gives off extreme heat or a burning odor.
- Use the battery only in Spectra Precision equipment that is specified to use it.

- Use the battery only for its intended use and according to the instructions in the product documentation.

Disposing of Rechargeable Lithium-ion Battery

Discharge Lithium-ion battery before disposing of it. When disposing of a battery, be sure to do so in an environmentally sensitive manner. Adhere to any local and national regulations concerning battery disposal or recycling.

Receiver Use and Care

The receiver can withstand the rough treatment that typically occurs in the field. However, the receiver is a high-precision electronic instrument and should be treated with reasonable care.

CAUTION - Operating or storing the receiver outside the specified temperature range can damage it. For more information, see Physical Specifications in this guide.

High-power signals from a nearby radio or radar transmitter can overwhelm the receiver circuits. This does not harm the instrument, but it can prevent the receiver from functioning correctly. Do not use the receiver within 400 meters (1312 feet) of powerful radar, television or other transmitters. Low-power transmitters such as those used in cell phones and two-way radios do not normally interfere with receiver operations.

For more information, contact your Spectra Precision distributor.

Bluetooth Radio

The radiated output power of the wireless radio is far below the FCC radio-frequency exposure limits. Nevertheless, the wireless radio shall be used in such a manner that the Spectra Precision receiver is 25 cm or further from the human body.

The internal wireless radio operates within guidelines found in radio-frequency safety standards and recommendations, which reflect the consensus of the scientific community. Spectra precision therefore believes the internal wireless radio is safe for use by consumers.

The level of energy emitted is far less than the electromagnetic energy emitted by wireless devices such as mobile phones. However, the use of wireless radios may be restricted in some situations or environments, such as on aircraft. If you are unsure of restrictions, you are encouraged to ask for authorization before turning on the wireless radios.

COCOM Limits

The US Department of Commerce requires that all exportable GNSS products contain performance limitations so that they cannot be used in a manner that could threaten the security of the United States.

The following limitation is implemented on the receiver: Immediate access to satellite measurements and navigation results is disabled when the receiver's velocity is computed to be greater than 1000 knots, or its altitude is computed to be above 17,000 meters (59,055 feet). The receiver continuously resets until the COCOM situation is cleared.

Technical Assistance

If you have a problem and cannot find the information you need in the product documentation, contact your local distributor. Alternatively, request technical support using the Spectra Precision website at www.spectraprecision.com.

Your Comments

Your feedback about the supporting documentation helps us improve it with each revision. Email your comments to documentation_feedback@spectraprecision.com.

Table of Contents

Introduction to Spectra Precision SP20	1
Discover Your SP20	3
Description	3
GNSS Antenna Height with Monopole	4
Optional Accessories	4
First-Time Use	5
Unpacking	5
Inserting the SIM Card, Micro SD Card and Battery	5
Turning On the SP20	7
Using the Universal Power Adapter to Charge the Battery	8
Attaching the Handstrap	9
Installing an Accuracy Option	9
Before Running Your GIS/Survey Application	9
Turning Off SP20	9
Using SSpace Software	10
Installing SSpace on your SP20	10
Starting SSpace for the First Time	10
Notes about the User Interface	11
Setting SP20 to Receive Corrections	12
SSpace Settings	13
Monitoring SP20 Operation	15
Operating Status Screens	15
Receiver Profile Status	17
Settings	18
External GNSS Antenna	18
SSpace vs. MobileMapper Field	18
SSpace vs. GNSS Loader	18
How to Hold the SP20	19
In Your Hand	19
On Top of a Monopole	19
On a Pole With External GNSS Antenna	20
Usual Android Settings and More	21
Choosing the Interface Language	21
Setting Time & Date	21
Adjusting Time to Screen Sleep Mode	22
Assigning Applications to the Programmable Buttons	22
Resetting SP20	23
Using GNSS Loader	24
Specifications	26
GNSS Characteristics	26
Real-Time Accuracy	26
CenterPoint RTX	27

FieldPoint RTX	27
Real-Time Performance	27
Post-Processing Accuracy	27
Data Logging Characteristics	27
Processor	27
Operating System	27
Memory	28
Communications	28
Interface	28
Environmental Characteristics	28
Power Characteristics	28
Physical Characteristics	29
Multi-Media & Sensors	29
Standard Accessories	29
Optional Accessories	29
Operating Modes	29
Field Software	30



The Spectra Precision SP20 handheld GNSS receiver combines innovative, camera-enabled data collection workflow with a high level of performance in an ergonomic, scalable solution from meter to centimeter accuracy. Rugged and lightweight, the SP20 is easy to use and highly accurate. It is the optimal tool not only for cadastral, construction or topo surveys, but also for a range of GIS projects, including data collection, inspection and maintenance.

The 5.3-inch screen delivers vivid visuals of the workflow, which enables precise 2D handheld logging. And the system's high degree of accuracy can be enhanced with a monopole accessory to deliver solid, survey-grade 3D measurements.

Whatever the type of geospatial work you will now be doing, you have made the choice of turning to an easy-to-use handheld that consistently delivers highly accurate results.

The **SP20 key features** are:

- **Integrated, high-accuracy GNSS** antenna and receiver complete with all communication devices (cellular modem, WiFi) for acquiring differential/RTK/Trimble RTX corrections when needed.
- **Ergonomic design:** High-performance, high-accuracy data collection in the palm of your hand.
- Powered by certified **Android 6 Operating System**. The additional, specific Android applications required are:
 - Spectra Precision *SPace* (available for free on Google Play). This Android application is required to interface SP20 with any third-party, standard Android applications (such as Spectra Precision *MobileMapper Field*) that make use of accurate positioning data as input. *SPace* takes control of the Android *mock location* parameter.
 - Spectra Precision *GNSSLoader* (available for free). This Android application is required to update the GNSS firmware and install firmware or accuracy options (with permanent or temporary validity).

- **Handheld accuracy**, position accuracy on demand. The SP20 is available in different configurations providing different position accuracies:
 - Meter (default) (standalone GNSS+SBAS)
 - Sub-meter (30/30)
 - Decimeter (7/2)
 - Centimeter (full RTK)

IMPORTANT NOTICE!

The SP20 is fitted with two distinct GNSS location providers:

- The *u-blox* Android GNSS
- The Spectra Precision high-accuracy GNSS module.

All location settings found in Android only impact the Android GNSS, not the high-accuracy GNSS module.

When starting the SP20, by default both the Android GNSS and the high-accuracy GNSS module are running. At this stage, any application you will be using will receive low-accuracy positions from the Android GNSS, and only from it. High-accuracy positions will be made available and used only if SPace – the specific Spectra Precision *mock location* provider – is started.



SPace may be started manually, or automatically when starting MobileMapper Field.

High-accuracy positioning will also be available for an application supporting direct access to the high-accuracy GNSS module. This will be the case with Spectra Precision Survey Mobile (through TPSDK).

As soon as SPace, or any TPSDK-based application, is started, the Android GNSS is made idle and the displayed location settings in Android are all irrelevant.

Discover Your SP20

Description Take a few minutes to discover your SP20.



This recess is designed to ease battery door ejection using the battery door opener provided (see First Time Use section).

- | | |
|--|---|
| [1] Built-in, high-precision GNSS antenna and receiver | [10] External GNSS antenna plug |
| [2] Android platform's 5.3" color touch screen | [11] Attachable/Detachable monopole adapter |
| [3] Headphone plug (underneath protection flap) | [12] Power button |
| [4] Programmable button A | [13] Camera lens (front) |
| [5] Programmable button B | [14] Camera lens (rear) and flash |
| [6] Micro USB (underneath protection flap) | [15] Speaker |
| [7] Reset button (underneath same protection flap) | [16] Lock button |
| [8] Microphone | [17] Battery door |
| [9] Volume control buttons | [18] Three attachment points for handstrap |

GNSS Antenna Height with Monopole



When used on top of the monopole accessory (see picture; the monopole adapter is secured to the back of the SP20, see also *page 3*), the SP20 can deliver accurate vertical coordinates because the monopole gives the SP20 excellent vertical stability.

When the monopole is used, the antenna height (H) you need to specify in your application (MobileMapper Field or Survey Mobile) is the length of the monopole (read the graduation on the monopole; see picture below).

For all Android applications using SSpace as interface, and when the monopole is used, you should enable **Use monopole** on the SSpace **Settings** screen.

The application will automatically add to H the distance (d) from the base of the monopole adapter to the phase center so that the application uses the real height of the GNSS antenna phase center above the ground.

Optional Accessories

Below is the list of optional accessories (Spectra Precision reserves the right to make changes to this list without prior notice):

1. Monopole (also known as half-pole):



Length is adjustable; three presettable lengths: 1.00 m (3.281 ft), 1.10 m (3.609 ft) and 1.20 m (3.937 ft).



2. Pole bracket:



3. External antenna cable (a coaxial cable):



Unpacking

The following items are delivered in the box:

- SP20 unit
- Li-Ion battery
- Universal power adapter (includes a USB-to-micro-USB cable)
- Quick Start Guide
- 2 x screen protectors
- Monopole adapter (an attachable 5/8-inch female adapter + 4 x Philips head screws)
- Handstrap
- Battery door opener (a black, rigid pen-shaped accessory)
- Pouch.

NOTE: Spectra Precision reserves the right to make changes to this list without prior notice.

Inserting the SIM Card, Micro SD Card and Battery

Follow the instructions below:


1. Turn over the SP20.
2. While exerting pressure on the battery door to ease the unlocking, slide out the lock using a finger or the tip of the battery door opener.



3. Insert the tip of the battery door opener into the recess (top-left corner of the battery door, see also *page 3*) and gently push the opener to release the door out of the unit.



4. Put the battery door away.
5. If you are using a SIM card or/and a Micro SD card, insert these items now, BEFORE inserting the battery, making sure these are oriented as instructed on the label, contact side facing down for each of them. Insert the SD card first, then the SIM card.



CAUTION: For a micro or nano SIM card, please use a rigid, not a flexible SIM card adapter. Flexible SIM card adapters may damage the SIM card slot.

6. Insert the battery as shown below. Orientate the battery so that its electric contacts come first into contact with those at the bottom of the battery compartment. Insert the contacts side of the battery first, as shown, then push the battery in.



(If you insert the battery the wrong way, the battery door won't close.)

7. Put the battery door back into place by first inserting the two lugs located at the bottom of the door (opposite the lock).



8. Then push the battery door against the unit and lock it.



Turning On the SP20

- Press the Power button [12] (see *page 3*) for a few seconds until the SP20 vibrates, then release the button.
- Depending on how long your product was stored in its package before being shipped to you, the remaining power in the battery may be too low to allow the SP20 to operate for your first working session. For this reason, the first thing to do is to check the **battery charge status**:
 - After the SP20 has started, read the battery icon in the Android notification bar at the top of the screen. The percentage of remaining charge is reported:




- If the remaining power is greater than 70%, then the SP20 can be used for your first job. If it is less, Spectra Precision recommends you first charge the battery as explained below before you go to the field.


Using the Universal Power Adapter to Charge the Battery

Follow the instructions below.

- Prepare the power adapter:
 - Choose the plug that fits your country's AC outlet standard (see [1]).



- Slide it into the AC adapter [2]. (A “click” must be heard when fully inserted.)
- Take the USB cable provided [3].
- Connect the end fitted with a standard USB connector to the power adapter.




- Connect the other end (fitted with a micro-USB connector) to the bottom side of the SP20 (open the flap [4] first).
- Connect the power adapter to an electric outlet. After about 4 seconds, the SP20 screen will light up showing a large battery icon being charged. The screen is then turned back off after about 10 seconds. After this time, battery charging will continue at the same rate until the battery is fully charged (charging time: 4 hours max.). The charger delivers a DC current of 2 A max. at 5 V DC.
- To read the battery charging status, just press briefly the power button to re-activate the screen for the next 10 seconds.

Attaching the Handstrap

The SP20 can more safely be hand-held using the handstrap (provided). The handstrap gives a better grasp and eliminates the risk of accidentally dropping the unit to the ground.

First you should attach the two ends of the handstrap to the back of the SP20. As shown below, there are two ways of attaching it. You'll choose one way or another, depending on whether you are left- or right-handed.

CAUTION - The ends of the handstrap are different. One is designed to be hooked to the center bottom of the unit, and the other to the right or left side of the unit.



Installing an Accuracy Option

This step is required if you have purchased the SP20 with position accuracy better than the default meter accuracy. You need to download and install *GNSSLoader* on the SP20.

GNSSLoader can be downloaded for free from Google Play or from the Spectra Precision website. For more information on GNSSLoader, refer to *page 24*.

Before Running Your GIS/Survey Application

Most Android applications, including Spectra Precision MobileMapper Field, will need SSpace as the software interface between your application and the SP20. SSpace can also be downloaded for free from Google Play. For more details, see *Using SSpace Software on page 10*.

On the other hand, some other applications (like Spectra Precision Survey Mobile) do not need SSpace as they integrate their own interface to the SP20.

Turning Off SP20

We recommend you neatly turn off the SP20 as explained below, which will avoid losing data.

After you have finished your work, turn off the SP20 by holding the Power button **[12]** pressed until a dialog pops up, inviting you to either power off, reboot or switch the SP20 to Airplane mode.

Touch **Power off** on the screen. This starts the power off procedure. Wait until the screen goes blank.

Using SPace Software



SPace is the software interface required when running Spectra Precision *MobileMapper Field* or a third-party Android application on the SP20.

SPace is mainly used to:

- Forward positioning information from the SP20 high-accuracy GNSS module to any application running on the SP20 and using the Android mock location server.
- Process incoming corrections.
- Monitor both GNSS reception, corrections reception and position accuracy.


Installing SPace on your SP20

SPace may be downloaded from Google Play (search for “Spectraprecision” applications and then find “SPace” in the list of available applications).

Follow the on-line instructions to install SPace on your SP20.


Starting SPace for the First Time

When launching SPace for the first time, a message will first ask you to read and accept the EULA agreement. Another message will follow asking you to choose the application providing Android with position information:




Touch **Yes**. This will open the list of developer options. Scroll down the screen until you find **Select mock location app** in the **Debugging** section.

Touch **Select mock location app**. This opens a dialog listing the apps that can be used for this purpose.



Touch **SPace**. The screen then shows that your choice is now active.



Press  to return to SPace (SKYPLOT tab displayed).
NOTE: You need to do this setting only once.

IMPORTANT- Whenever you launch SPace, including the first time you do it, it takes about 4 seconds before the SP20 gets initialized. During this time, the antenna icon in the SPace status bar looks like this:



When initialization is complete, this icon changes aspect to look like this:



Notes about the User Interface

You will find the following graphic objects in SPace. The table below explains what they are for and when and how to use them:

Object	Function
	This is a switch: An empty circle stuck to the left means the concerned parameter is disabled while an orange circle stuck to the right means it is enabled. To switch from one state to the other, just touch the line including this graphic object or simply drag the circle to the left or right.
	This object is associated with the previous one. After making a choice with the above switch, touch this button in the lower-right corner of the screen to save the change or changes you've just made. This will take you to the previous screen.
	Please wait when this animated object is displayed. That means the SP20 is being interrogated and it takes a while before the requested information is returned. Normally this item disappears after a few seconds.

Setting SP20 to Receive Corrections

After the SP20 has initialized, do the following to set it up (see also *SPace Settings* on page 13 to have a global view of all the settings you can make in SPace):

- In the status bar, touch .
- Touch the **Correction Information** field. You are then requested to choose between different sources of corrections:

Source of corrections	Meaning
SBAS	Corrections will be received from an SBAS satellite.
NTRIP	Corrections will be received from a particular mount point part of an NTRIP network, via the Internet.
DIP	Corrections will be received from a base via the Internet.
RTX IP	Corrections will be received from a Trimble RTX service via the Internet (RTX IP mount point (worldwide) or RTXEU mount point (Europe only). A valid subscription to a Trimble RTX service is required (1).
RTX L-BAND	Corrections will be received from a Trimble RTX service via an RTX satellite. A valid subscription to a Trimble RTX service is required (1).

(1) You can check the current status of your RTX subscription on the **Receiver Information** screen by touching  in the SPace title bar.

- Choose the desired source of corrections, and then touch the horizontal right arrow in the lower-right corner of the screen.

1. **If you chose SBAS:** No additional setting is required.

2. **If you chose NTRIP:** The first time you want to make an NTRIP connection, there is no predefined connection profile available. Touch the “+” symbol in the lower-left corner of the screen and then enter the parameters of your NTRIP provider:

Friendly Name (max 20 chars): Freely choose a convenient name for this connection profile.

Host Name or IP Address (The host name should contain a valid domain name.)

Port Number

Touch the **Get Source Table** button to list the mount points available from this provider and select one. If you remember the name of the mount point you want to use, you don't need to acquire the source table: Just touch the **Enter Mount Point** button and type in the name of the desired mount point.

Then enter your NTRIP credentials (**User Name** and **Password**).

Touch **Connect** at the bottom of the screen. At this point, SSpace will initiate a network connection to allow the SP20 to receive corrections from the chosen NTRIP provider.

3. **If you chose DIP:** The first time you want to make a DIP connection, there is no predefined connection profile available. Touch the “+” symbol in the lower-left corner of the screen and then enter the parameters of your DIP provider:

Friendly Name (max 20 chars): Freely choose a convenient name for this connection profile.

Host Name or IP Address (The host name should contain a valid domain name.)

Port Number

Touch **Connect** in the lower part of the screen. At this point, SSpace will initiate a point-to-point network connection to allow the SP20 to receive corrections from the chosen static IP address.

4. **If you chose RTX IP:** Select the Trimble RTX mount point to connect to RTXIP (for worldwide coverage), or RTXEU (for European coverage only). You also need a valid subscription to a Trimble RTX service.
5. **If you chose RTK L-BAND:** There are no additional settings required, but you need a valid subscription to a Trimble RTX service.

NOTE: Next time you turn on the SP20 for a new working session, the last NTRIP or DIP network connection made will be re-established automatically, provided you still have the required environment (modem, Wi-Fi) to establish a network connection.

SSpace Settings

- In the status bar, touch .
 - Set the following parameters:
 - **Autostart application at boot:** Enabling this parameter means SSpace will be started automatically next time you power up your SP20. This way, you don't have anything else to do at power up, but start your application as soon as the SP20 is ready to operate. If you disable this parameter, SSpace will run only if you start it manually or if you start MobileMapper Field.
- NOTE:** Whatever this setting, SSpace will be stopped automatically when you quit MobileMapper Field.

- **Receiver** (a read-only field): Displays the product name (“SP20”).
- **Correction Information:** Source of corrections currently used. If you touch this line, you may change the type of connection through which corrections enter the SP20 (SBAS, NTRIP, DIP, RTX IP or RTX L-BAND; see *page 12* for all the details). By touching the “+” symbol after selecting “NTRIP” or “DIP”, you may add a new NTRIP or DIP provider respectively.
- **Use monopole:** By activating this function, you allow the SP20 to deliver 3D positioning, the height of the SP20 above the ground being accurately known in that case.
- **External antenna model** (only if an external GNSS antenna is connected to the SP20 via plug **[10]** (see *page 3*): Choose the model of external GNSS antenna used from the available list (possible antenna models are 111660, 111661, SPGA Rover, Zephyr 3 Rover). Logically, when this option is visible in **Settings**, then **Use monopole** (above) is not.
- **Configuration File:** Allows you to run a file containing a set of commands intended to modify the configuration of the high-accuracy GNSS module. The file should be a text file with the “txt” extension and should have been saved to the Download folder. To have the receiver executing the desired set of commands, just touch the txt file containing this set of commands. The response of the high-accuracy GNSS module to the set of commands will be returned in a file named “<file_name>.txt.log”, also visible in the Download folder.
- **RF Band selection:** Touch this parameter to choose which GNSS frequencies to receive (L1, L2, L-Band). L1 and L2 are enabled by default and L-Band is disabled by default. L1 cannot be disabled.
- **Constellation tracking:** Touch this parameter to choose which constellations to receive (GPS, GLONASS, Galileo, SBAS, BeiDou, QZSS). By default, all constellations are used (enabled).
- **Debug Data Recording:** Enable or disable the automatic recording of ATL data (debug data). Enabling this function makes sense only if Spectra Precision technical support requires to do so. Otherwise keep it disabled. Debug data will be saved as an ATL_yymmdd_hhmmss.log file stored in folder:
 .../Download/ATL Data/

e.g. ATL180524_141126.log created at 2:11:26pm on May 23, 2018.

- **Keep NMEA outputs running:** When enabled, this option makes sure all the NMEA messages delivered by the GNSS receiver to SSpace continue to be output while SSpace is running and after SSpace has stopped running.
- **Help:** Touch this line to open the Help page. Use the Back key on the SP20 to close the Help page.
- **About:** Touch this line to read the installed SSpace software version.

Monitoring SP20 Operation

Operating Status Screens



The **SKYLOT** tab ([1]) is a polar diagram showing the location in the sky of each tracked satellite.

Touch **Legend** ([4]) to read the color convention used for each constellation to represent satellite locations on the skyplot view:



In the lower part of the screen, you can read the total number of currently tracked satellites and total number of satellites currently used.

The **POSITION INFORMATION** tab ([2]) provides the following information, from top to bottom:

- Receiver name (SP20)
- Latitude and Longitude of current position
- Altitude of current position
- Geoidal separation (vertical distance between datum used and geoid used)
- HRMS, VRMS: Horizontal and vertical errors
- Speed: SP20 speed, in meters/second
- Fix quality: Position computation mode (**AUTONOMOUS**, **DGPS**, **FLOAT RTK**, **FIXED RTK**).

The **CORRECTION INFORMATION** tab ([3]) provides the following information, from top to bottom:

- **Host Name or IP Address:** Identification of the NTRIP, DIP or RTX server providing the corrections used.
- **Port Number:** IP port number of the NTRIP, DIP or RTX server providing the corrections used (blank for SBAS) (the presence of a hyphen in any field means "Blank").
- **Type:** Type of connection used (SBAS, NTRIP, DIP or RTX) to let SP20 acquire corrections.
- **Mount Point:** Name of mount point used in NTRIP or RTX (blank for SBAS and DIP).
- **Network:** Indicates which medium (**Mobile** or **Wi-Fi**) is used to make a network connection (blank for SBAS).

- In the same line:
 - **Age:** Age of the corrections received, in seconds.
 - **Station ID:** Identification number of the station, or PRN of satellite in SBAS, or RTX satellite ID, providing the corrections used.
- **Status:** Network connection status (**Connected** or **Disconnected**) (Blank if SBAS).

Receiver Profile Status



: Touch this icon (see [5] on *page 15*) to read information about the SP20:

- **Receiver Type:** “SP20”.
- **GNSS Connection Status:** “Connected” necessarily. At power up, as long as this connection is not active, you cannot open this window. The receiver icon then looks like this:



NOTE: After launching SPace, it takes about 4 seconds before this connection is active.

- **RTX Subscription:** Provides the current status of your subscription to an RTX service (available at a later date):
 - **Valid until <date>:** You are currently allowed to use an RTX service. The subscription will expire at the specified date.
 - **Expired:** Subscription expired. You need to renew your subscription if you wish to resume using this RTX service.
 - **Invalid:** Your receiver has never been allowed to decode RTX corrections. If you want your receiver to do so, you need to subscribe to an RTX service (available at a later date).
- **MSL version:** Software version of SP20 Micro Service Layer. (This piece of software is used to interface SP20 with Android).
- **RTK Option:** Indicates the level of precision available from your SP20:
 - **Full RTK** (centimeter accuracy): Centimeter-accurate 3D position
 - **7/2** (decimeter accuracy): Accuracy is 7 cm in horizontal and 2 cm in vertical

- **30/30** (sub-meter accuracy): Accuracy is 30 cm in both horizontal and vertical.

- **RTX Option:** Indicates whether a Trimble RTX subscription is valid (“CenterPoint RTX” or FieldPoint RTX” is displayed) or not (“None” is displayed).

NOTE: RTK options may have temporary validity (1 month).

Settings

See *page 13*.

External GNSS Antenna



This icon (see [7] on *page 15*) is shown only if an external GNSS antenna has been connected to the SP20 (see plug [10] on *page 3*).

If you touch this icon, you will be able to read the connection status and the signal level, as received by this antenna.

SPace vs. MobileMapper Field

SPace is started automatically when launching MobileMapper Field. However only the section of SPace delivering accurate positions will be run in this case. That means SPace will actually work as a position server for MobileMapper Field, but its own user interface will not be running. The consequence is that SPace will not be seen by Android as a running application.

NOTE: The SPace position server will be closed automatically when quitting MobileMapper Field.

If you need to view what the current GNSS reception status is while using MobileMapper Field, you will have to open the SPace window to access this information. You may do this by touching the SPace icon (below left) in the Android applications menu, or by touching this icon (see below right) in the Android notification bar:



SPace vs. GNSS Loader

To start GNSSLoader⁽¹⁾ (see *page 24*), which will be successful only if SPace is NOT running, you will also have to open the SPace window as indicated previously in order to be able to quit SPace and then launch GNSSLoader.

1.Or any other application having direct control over the SP20 high-accuracy GNSS module.

How to Hold the SP20

In Your Hand

This requires that you hold the SP20 in an appropriate manner. The SP20 will have the best view of the sky if you hold it at waist level (or higher), at such an angle that the top of the unit (containing the GNSS antenna; see [1], page 3) is in horizontal position and not too close to your body.



On Top of a Monopole

First attach the monopole adapter to the back of the unit. Use a Philips screwdriver and the four screws provided to secure the adapter. Mount the SP20 on top of the monopole (optional accessory).



The SP20 will have the best view of the sky if you hold it not too close to your body.

On a Pole With External GNSS Antenna

In cases where you wish to use an external GNSS antenna mounted on top of a pole, the SP20 will be inserted into a bracket (optional accessory) which you will fasten to the pole, approximately at mid-height.

You can freely orientate the SP20 on its bracket since it is the external GNSS antenna, and not the SP20's own antenna, that is used in this case.



Insert the SP20 into the bracket so that it is pinched where you would normally hold it in your hand. That way you keep the rear camera clear and preserve access to the Power button.

You may use one of the two notches in the bracket to attach the coaxial cable connecting the SP20 to the external GNSS antenna (see above picture), thus protecting the coaxial connector on SP20 side from being accidentally pulled out.

To remove the SP20 from the bracket, hold the external jaw of the bracket firmly in one hand and extract the SP20 from the bracket using the other hand.

Literature about Android 6 can easily be found on the Internet. If you are new to Android, you may consult this information on line. Below are suggestions of links you may use to learn more about Android 6:

<https://www.cnet.com/how-to/roasting-marshmallow-your-guide-to-android-6-0/>
<https://www.android.com/versions/marshmallow-6-0/>

Many other sources of information exist on the Internet that you can find by yourself.

This section only describes a few basic Android functions you may need to use while working with your SP20.

Choosing the Interface Language

- From the Android welcome screen, touch  then .
- Scroll down to the **Personal** section and once visible, touch the line containing this icon: .
- In the first field at the top of the screen, select your language.
- Touch  repeatedly to return to the Android welcome screen.

Setting Time & Date

Following a battery change in the field with no network connection, the Android time & date is likely to be wrong (because not automatically updated). Although as soon as GNSS reception is re-established, raw data (if recorded) will be properly time-tagged, on the other hand the creation time and date of the raw data file will remain wrong.

If however you can temporarily get a WiFi or GSM connection from your SP20, then you will allow the Android time & date to be automatically updated.

But if this is not possible, we recommend you set the Android time and date manually before resuming your work so that the files you will subsequently create are all properly dated.

- From the Android welcome screen, touch  then .
- Scroll down to the **System** section and once visible, touch the line containing this icon: .

- Momentarily disable the **Automatic date & time** parameter and then enter successively the current date and time in the fields located underneath.
- Then re-enable the **Automatic date & time** parameter.
- Touch  repeatedly to return to the Android welcome screen.

Adjusting Time to Screen Sleep Mode

When using your SP20 in the field, there may be long periods of time during which your SP20 is collecting data but there is no need for you to touch the screen during this time (for example you are collecting a long line or polygon feature with MobileMapper Field). In this case you may want to keep the screen awake throughout the logging sequence.

The default time for the screen to switch to sleep mode being only 1 minute of inactivity, you will probably want to change this time. Here is how you can do this:

- From the Android welcome screen, touch  then .
- Scroll down to the **Device** section and once visible, touch the line containing this icon: .
- Touch the fourth field (**Sleep**) and then choose the duration of inactivity at the end of which the screen will turn blank. The longest time you may choose is 30 minutes of inactivity.
- Touch  repeatedly to return to the Android welcome screen.

NOTE: The fact that the screen switches to sleep mode has no impact whatsoever on any data collection sequence taking place in the SP20.

Assigning Applications to the Programmable Buttons

(See programmable buttons A and B on *page 3*.)

- From the Android welcome screen, touch  then .
- Scroll down to the **Personal** section and once visible, touch the line containing this icon:  (**AB Key Set**).
- Touch button A or B at the top of the screen then tick one of the apps listed below that you want to assign to the corresponding key (e.g. Calculator). Repeat this action for the other key if you wish (e.g. E-compass).
- Touch  repeatedly to return to the Android welcome screen.

Resetting SP20

In the very unlikely case where your SP20 would stop responding and a press on the power button would have no effect, then you might conveniently use the reset button for a fresh restart of the unit without having to temporarily remove the battery.

The reset button is that miniature button nested close to the USB connector (see **[7]** on *page 3*). To press this button use a thin, long and pointy tool, like for example a pencil or an unfolded paper clip.

After pressing the button, the SP20 will simply restart. This action has no effect whatsoever on your Android settings, your applications, files and personal data. It's just a hardware reset.

Using GNSS Loader

This application is required whenever you need to update the SP20's GNSS firmware and/or if you have purchased the SP20 with better than one meter position accuracy. GNSSLoader will be used in the latter case to install the corresponding firmware option.

GNSSLoader can be downloaded for free from the Spectra Precision website or from Google Play at:

<https://play.google.com/store>

Follow the instructions to install GNSSLoader on your SP20. Then run GNSSLoader by touching this icon in the Android applications menu:



The GNSSLoader menu includes the following functions:

- **Reset GNSS:** Touch this option to reset the SP20's built-in, high-accuracy GNSS receiver. When the sequence is complete, this message is displayed:

Complete

GNSS has been reset to the default settings

Touch **OK** to close the message dialog box and return to the main menu.

- **Upgrade firmware:** Opens a window listing the possible GNSS firmware upgrades currently stored in the Download folder. These files use the following naming convention:

SP20_upgrade_vx.xx.x.tar

Where vx.xx.x is the firmware version contained in the upgrade file.

(So you should have downloaded your GNSS firmware upgrade from the Spectra Precision website to the Download folder before using the **Upgrade firmware** function.)

To install an upgrade select the file and then touch ➡.

- **Install accuracy option:** Opens a window listing the currently installed accuracy options.

The **ADD** button located at the bottom of the screen allows you to install a new option after entering the corresponding POPN.

The following screen appears after touching **ADD**:

If you have purchased your SP20 with sub-meter, decimeter or centimeter accuracy, you should have received the corresponding POPN via email.

Enter the POPN and touch **INSTALL**.

- **Install service or other option:** Same as **Install accuracy option**. This function needs a passcode, which is used to activate the Trimble RTX service for which you have purchased a subscription.

- **About:** Returns the software version of the installed GNSSLoader application, the SP20 unit serial number and the version of the GNSS firmware currently installed in your SP20. Touch **OK** to return to the main menu.

NOTE: GNSSLoader cannot be started while SPace is running. If you try to do so, a message will appear informing you that this is not possible.

Specifications

GNSS Characteristics

- 240 GNSS channels
 - GPS L1, L2 (L1 C/A, L1P, L2P/ L2C)
 - GLONASS G1, G2 FDMA
 - BeiDou B1 (phase 2 and phase 3), B2 (phase 2)
 - Galileo E1, E5b
 - QZSS L1C/A, L2C, L1Z
 - SBAS L1C/A
 - L-Band: 2 channels
- Scalable accuracy, from meter to centimeter (meter, sub-meter (30/30), decimeter (7/2), centimeter (full RTK)).
- Patented Z-Blade technology for optimal GNSS performance
 - Full utilization of signals from all 6 GNSS systems (GPS, GLONASS, BeiDou, Galileo, QZSS and SBAS)
 - Enhanced GNSS-centric algorithm: fully-independent GNSS signal tracking and optimal data processing, including GPS-only, GLONASS-only or BeiDou-only solution (autonomous to full RTK).
 - Fast search engine for quick acquisition and re-acquisition of GNSS signals.
- Patented SBAS ranging for using SBAS code & carrier observations and orbits in RTK Processing.
- Patented Strobe™ Correlator for reduced GNSS multi-path.
- Supported data formats: ATOM, CMR, CMR+, RTCM 2.1, 2.3, 3.0, 3.1 and 3.2 (including MSM), CMRx and sCMRx.

Real-Time Accuracy

(RMS)(1)(2)

SBAS (WAAS/EGNOS/MSAS/GAGAN):

- Horizontal: < 50 cm
- Vertical: < 85 cm

Real-Time DGPS position:

- Horizontal: 25 cm + 1 ppm
- Vertical: 50 cm + 1 ppm

Real-Time Kinematic Position (RTK) (3):

- Horizontal: 10 mm + 1 ppm
- Vertical: 15 mm + 1 ppm

CenterPoint RTX

(1)(2)

- Horizontal: 4 cm (0.13 ft)
- Vertical: 9 cm (0.29 ft)
- Convergence time: 30 minutes or less (6).

FieldPoint RTX

(1)(2)

- Horizontal: 20 cm (0.33 ft)
- Vertical: 9 cm (0.29 ft)
- Convergence time: 15 minutes or less (6).

Real-Time Performance

- Instant-RTK® Initialization:
 - Typically 2 sec for baselines < 20 km
 - Up to 99.9% reliability
- RTK initialization range: over 40 km.

Post-Processing Accuracy

(RMS)(1)(2)

Static & Fast Static:

- Horizontal: 3 mm + 0.5 ppm
- Vertical: 5 mm + 0.5 ppm

High-Precision Static (4):

- Horizontal: 3 mm + 0.1 ppm
- Vertical: 3.5 mm + 0.4 ppm

Data Logging Characteristics

Recording interval:

- 1 - 999 seconds

Processor

- Qualcomm Snapdragon 410
- Quad-core
- Clock frequency: 1.2 GHz

Operating System

- Android® 6.0 (Google certified)
- Languages available: Afrikaans, German, English, Spanish, French, Italian, Portuguese (Portugal and Brazil), Japanese, Korean, Simplified Chinese, Greek, Russian, Azerbaijani, Czech, Danish, Lithuanian, Hungarian, Dutch, Norwegian (Bokmal), Romanian,

Finnish, Swedish, Turkish, Bulgarian, Serbian (Cyrillic), Hindi, Polish.

- Software package includes Google Mobile Services.

Memory

- 2 GB SDRAM
- Storage: 16 GB (non volatile).
- MicroSDHC™ memory card (up to 64 GB, SanDisk®, KingstonR recommended).

Communications

- Cellular:
 - GSM (850,900,1800,1900), GPRS, EDGE, UMTS, WCDMA (B1, B2, B5, B8), HSPA, TDSCDMA (B34, B39), LTE-FDD (B1, B3, B4, B5, B7, B8, B20), LTE-TDD (B38/B39/ B40/B41)
- Wi-Fi (IEEE) 802.11 b/g/n
- Bluetooth 4.0 dual mode
- USB (micro B USB connector)
- NFC.

Interface

- USB 2.0 (micro)
- External GNSS antenna connector (TNC)
- Audio jack 2.5 plug (CTIA/AHJ standards).

Environmental Characteristics

- Operating temperature: -20° to +60°C (-4 to 140°F)
- Storage temperature: -30° to +70°C without battery (-22 to 158°F) (5)
- Humidity: 95% non condensing
- Water & dust proof: IP67
- Free drop: 1.2 m on concrete
- Shocks: MIL STD 810 (fig 516.5-10) (01/2000)
- Vibration: MIL-STD-810F (fig 514.5C-17) (01/2000)

Power Characteristics

- Battery Li-Ion, 6400mAh
- Battery life: > 8 hrs @ 20 °C with GNSS on
- Charging time: 4 hours
- Removable battery.

Physical Characteristics

Size:

- 29.5 x 12 x 4.5 cm (11.6 x 4.7 x 1.8 in)

Weight:

- 850 g (1.87 lb)

User Interface:

- 2 volume keys, on/off/reset key, 2 programmable keys, standard Android touch panel buttons
- On screen keyboard display
- Size: 5.3" capacitive multi touch
- Resolution: 1280 x 720 pixels
- Brightness: 450 Cd/m²
- Gorilla Glass damage-resistant
- Auto-rotate between Portrait and Landscape.

Multi-Media & Sensors

- Rear camera, 13 megapixels, with flash light
- Front camera, 2 megapixels
- E-Compass
- G-sensor
- Speaker
- Microphone
- Light sensor.

Standard Accessories

- Handstrap
- Screen protectors (x2)
- A/C charger
- USB cable
- Pouch
- Battery door opener
- Monopole adapter

Optional Accessories

- External GNSS antenna
- Pole bracket
- Monopole.

Operating Modes

- RTK rover: Direct IP, NTRIP (VRS, FKP, MAC networks)
- Post-processing
- Trimble RTX (IP and satellite).

Field Software

- Survey Mobile (SPSM)
- MobileMapper Field
- or third-party Android applications.

(1) Accuracy and TTFF specifications may be affected by atmospheric conditions, signal multipath, satellite geometry and corrections availability and quality.

(2) Performance values assume minimum of five satellites, following the procedures recommended in the product manual. High multipath areas, high PDOP values and periods of severe atmospheric conditions may degrade performance. Real-time accuracy depends on the SP20 accuracy option installed. Post-processing (PP) accuracy obtained with ATOM files processed by SPSO.

(3) SP20 used with monopole accessory.

(4) Long baselines, long occupations, precise ephemeris used.

(5) Battery can be stored up to +70°C.

(6) Receiver convergence time varies based on GNSS constellation health, level of multipath, and proximity to obstructions such as large trees and buildings. Convergence can be improved in RAM enabled regions.

Index

Numerics

30/30 2, 18

7/2 2, 17

A

Accuracy 2

Accuracy figures 26

Accuracy option 9

Age 17

Android 6 1, 21

AUTONOMOUS 16

Autostart application at boot 13

B

Battery door opener 5

Battery status 7

C

Cameras 3

CenterPoint RTX 27

Centimeter (accuracy) 2

Configuration file 14

Constellation tracking 14

Correction information 16

D

Debug data recording 14

DGPS 16

DIP 13

E

External GNSS antenna (setup) 20

F

FIXED RTK 16

FLOAT RTK 16

G

GNSS antenna (built-in) 3

GNSS antenna (external) 14

GNSS characteristics 26

GNSS connection status 17

GNSS external antenna plug 3

GNSS receiver (built-in) 3

GNSSLoader 1, 18, 24

H

Handstrap 5, 9

Handstrap (attachment points) 3

Help 15

Holding the receiver properly 19

I

Inserting battery 6

Install accuracy option 24

Interface language 21

K

Keep NMEA outputs running 15

Key features 1

L

Legend (skyplot) 16

M

MobileMapper Field 1

Mock location 10

Modem (cellular) 28

Monopole 3, 5, 14, 19

Mount point 12

MSL 17

N

NTRIP 12

O

Opening battery door 5

P

Phase center 4

Pole bracket 4, 20

POPn 1, 24

Position information 16

Pouch 5

Power button 3

Power Off 9

Programmable buttons 22

R

Recovering time & date manually following battery change 21

Reset 3, 23

Reset GNSS 24

RF Band selection 14

RTK 17

RTX option 18

RTX subscription 17

S

SBAS 12, 13

Screen timeout (controlling) 22

SD card 6

SIM card 6

Skyplot 15

Source table 12

SPace 1, 9, 10, 18

Station ID 17

System time & date 21

T

Temperatures 28

U

Universal AC adapter 5

Upgrade firmware 24

USB 28

Use monopole 14

User Guide

Contact Information:

AMERICAS

10368 Westmoor Drive
Westminster, CO 80021, USA
+1-720-587-4700 Phone
888-477-7516 (Toll Free in USA)

EUROPE, MIDDLE EAST AND AFRICA

Rue Thomas Edison
ZAC de la Fleuriaye - CS 60433
44474 Carquefou (Nantes), France
+33 (0)2 28 09 38 00 Phone

ASIA-PACIFIC

80 Marine Parade Road
#22-06, Parkway Parade
Singapore 449269, Singapore
+65-6348-2212 Phone



www.spectraprecision.com

©2018, Trimble Inc. All rights reserved. Spectra Precision and the Spectra Precision logo are trademarks of Trimble Inc. or its subsidiaries. All other trademarks are the property of their respective owners. (2018/07)