



# Tripltek 9 Power FAQ

## DESCRIPTION

### How long with the Tripltek 9 Pro run LandStar 8?

Mark Silver, [ms@igage.com](mailto:ms@igage.com), May 15 2025

Filename:Tripltek9ProPowerFAQ.docx

## Setup

TT9 connected to a i93 receiver by Bluetooth, with Wi-Fi connected to office Wi-Fi.

LandStar8 Version 8.1.0.5.20250123.

Display turned to full brightness with the Screen timeout = Never; Adaptive brightness = Off.

Survey > Continuous Survey > Interval set to 30 seconds

A web camera with an SD card for storage was pointing at the tablet. So, it is possible to verify that the collector screen was powered on the entire test.

## Summary

|                               |             |           |
|-------------------------------|-------------|-----------|
| Survey began at 7:34 pm       | TT9P = 100% | i93 = 93% |
| At 10:04 pm                   | TT9P = 77%  | i93 = 75% |
| Display turned off at 4:04 am | TT9P = 2%   |           |
| At 07:00                      |             | i93 = 47% |

The Survey stored 1040 points, 520 minutes, 8 hours 40 minutes.

## Charging Cycle

The TT9P was plugged into the factory charger at 7:00 am and registered 2% battery charge. At 8:28 the battery was at 85% charge, this is 0.9% per minute or 60% charge per hour.

## Power Related Settings



